



Voltage/Continuity Tester Eazyvolt+

2 pole voltage tester

The EazyVolt Plus is a reliable and safe 9-in-1 automatic voltage tester up to 750 V, with functions:

- Measuring AC Voltage
- Measuring DC Voltage
- Resistance
- Frequency
- Phase detection
- Continuity and diode
- Phase rotation
- RCD test by phase- earth (once charged)

Self-test by switch

Features of EazyVolt Plus

- Fully automatic
- Flashlight / torch by ultra bright LED
- 3 Phase rotation by 2 probes
- Selectable probe tips 2...4 mm.
- Dual display for VAC and Hz
- Water proof (IP65)
- Fail safe (no battery for VAC / DC measurement)
- Schuko compliant (19 mm)

1-hand operation by IP2X

Including

- Batteries
- Manual



Specificaties

Overvoltage protection	CAT III 1000 V / CAT IV 600 V
Supply	2x AAA, 1.5 V battery
LCD Resolution	1 V
Drop proof	1 meter
Voltage detection	Automatic
Response time	< 0.1 s/BAR < 2 s/RDG
Continuity	< 200 Ω
Auto power on	> 12 VAC/DC
IP protection	IP65 pending
Standard	EN 61010-1 / -031, EN 61243-3, EN 60529, EN 61557-7/-10/-1, EN 61326, EN 55011
Dimensions	239 x 68 x 29 mm
Weight	235 g (incl. batteries)

Function	Range
Voltage	12...750 VAC ($\pm 1.3 \% + 5d$) 12...750 VDC ($\pm 1.0 \% + 2d$)
Frequency	1...999 Hz ($\pm 0.3 \% + 5d$)
Resistance	0...2 K Ω ($\pm 2 \% + 2d$)
RCD check	



WEB: www.austutilities.com.au
EMAIL: sales@austutilities.com.au

PHONE: 08 9406 3200